

Proof of intrinsic safety

For intrinsically safe circuits with a supply.

device:

Jellox Analog xx

associated equipment:

Manufacturer	Type	Device	EU type examination certificate	ATEX marking
Microtronics	D012-x1***2***05	Rugged GW Analog	SIQ 24 ATEX 212 X	<Ex> II 2G Ex ib IIB T3 Gb

max. output voltage
max. output current
max. output power
max. external capacity
max. external inductance

U _o [V]=	25,6
I _o [A]=	0,082
P _o [W]=	0,523
C _o [nF]=	310
L _o [μH]=	1000

50% rule is to be applied,
as C_i > 1% of C_o and/or L_i > 1% of L_o

red. capacity C_o [nF]= 155
red. inductance L_o [μH]= 500

intrinsically safe equipment:

Manufacturer	Type	Device	EU type examination certificate	ATEX marking
Rosemount	248	Temperature transmitter	Baseefa18ATEX0090X	<Ex> II 1G Ex ia IIC T5/T6 Ga

max. input voltage
max. input current
max. input power
max. internal capacity
max. internal inductance

U _i [V]=	30
I _i [A]=	0,13
P _i [W]=	1
C _i [nF]=	3,6
L _i [μH]=	0

cable + pressure compensation element:

Manufacturer	Type	length [m]
Lapp	Öfflex EB CY 7x0,75	137

cable capacitance [nF/m]
cable inductance [μH/m]:

0,98
3,64

resulting cable capacitance
resulting cable inductance

C _c [nF]=	134,26
L _c [μH]=	498,68

safety-related values of the interconnection:

D012-x1***2***05		248		Intrinsic safety fulfilled
25,6	U _o ≤ U _i	30	V	YES
0,082	I _o ≤ I _i	0,13	A	YES
0,523	P _o ≤ P _i	1	P	YES
155	C _o ≥ C _i + C _c	137,86	nF / IIB	YES
500	L _o ≥ L _i + L _c	498,68	μH / IIB	YES

For use in EPL
"Gb" (category
2G) and group
IIB

Special conditions in the type examination certificate or in the manual of the associated / intrinsically safe equipment must be observed.
The proof of intrinsic safety is based on the safety-related maximum values. These were taken from the manual or the EC type examination certificates for the equipment.

Configuration recommendation:

The recommendation refers to the configuration of your Jellox product. You can make the settings in the platform.
Please refer to the table at <https://support.microtronics.com/jellox-analog/compatible-sensors> for the configuration recommendation.



The recommendation refers to the configuration of your Jellox product. You can make the settings in the platform.

Document revision

version	date	name	change	reason
01v000	14.05.2025	AZ	all	building document

Release

number	date	name	activity	signature
1	14.05.2025	AZ	created	
2			approved	